



PowerTech Generator Maintenance Checklist

Use this checklist before and during scheduled generator maintenance. Check off each task as it is completed to ensure optimal performance and reliability.

Before Every Start

- ☐ Check engine oil level
- ☐ Check coolant level in radiator (not just overflow bottle)
- ☐ Ensure at least 0.5" coolant in overflow bottle
- ☐ Inspect for visible leaks or loose connections

First 50 Hours

- ☐ Change engine oil
- ☐ Replace oil filter
- ☐ Replace fuel filter

Every 100 Hours

- ☐ Change engine oil
- ☐ Replace oil filter

Every 500 Hours

- ☐ Replace fuel filter
- ☐ Replace air filter
- ☐ Visually inspect air filter for early clogging

Every 2 Years

- ☐ Replace all belts
- ☐ Replace all hoses

Annually

- ☐ Inspect mounts for tightness
- ☐ Check for corrosion on electrical connections and mounts

Additional Notes

- ☐ Use 15W-40 oil for all PowerTech generators
- ☐ Use Orange 50/50 Dex-Cool Antifreeze
- ☐ Prime generator after changing fuel filter to eliminate air in the lines